

SUN.433**Descrizione**

Grazie alla sua ampia gamma di compatibilità, il trasmettitore **SUN.433** è sicuramente il telecomando più duttile e universale presente ad oggi sul mercato.

I pulsanti del telecomando sono completamente indipendenti fra di loro, in questo modo è possibile memorizzare, in 4 diversi tasti, 4 diverse frequenze o 4 diversi brand, anche tutte diversi fra di loro.

Per ogni pulsante si può memorizzare:

- **Qualsiasi Brand;**
- **Codici fissi;**
- **Rolling code.**



Frequenza	433 MHz
Canali	4 canali indipendenti
Codici duplicabili	Codici fissi e rolling code
Alimentazione	1 batteria al litio 3 V – Tipo CR2032 (Inclusa)
Dimensioni	36 x 54 x 12 mm
Peso	30 g
Programmazione	Auto-apprendimento
Memoria	Riscrivibile e resettabile in qualsiasi momento

Duplicazione

1. Posiziona il radiocomando originale ed il **SUN.433** molto vicini l'un l'altro;
2. Premi e mantieni premuti sia il pulsante del radiocomando originale da clonare sia il pulsante del **SUN.433** sul quale si vuole memorizzare il codice fino a quando il led del **SUN.433** inizia a lampeggiare velocemente;
3. A quel punto è possibile rilasciare entrambi i pulsanti e l'operazione è conclusa;
4. Ripetere l'operazione per duplicare altri radiocomandi.

Eliminare i codici memorizzati

1. Premere e mantenere premuti il pulsante 1 ed il pulsante 2 del **SUN.433** finché il led inizia a lampeggiare;
2. A quel punto mantenere premuto il pulsante 1 e nel frattempo premere tre volte il pulsante 2.
3. Per verificare il successo dell'operazione è sufficiente premere uno dei pulsanti sul quale prima era memorizzato un codice e verificare che, alla pressione del pulsante, il led non lampeggi.

Ripristinare codici cancellati

Attenzione: questa operazione ripristinerà soltanto gli ultimi 4 codici cancellati sui rispettivi pulsanti.

1. Premere e mantenere premuti il pulsante 3 ed il pulsante 4 del **SUN.433** finché il led inizia a lampeggiare;
2. Il led smetterà di lampeggiare segnalando l'esito positivo dell'operazione.

Domotime srl

Via Monico, 9 25017 Lonato d/G (BS) – Italy –

Tel: +39 030 9913901 - Fax: +39 030 2070611

Skype: domotime - email: info@domotime.com - www.domotime.com

SUN. 433

Description

Thanks to its wide range of compatibility, the SUN.433 transmitter is certainly the most flexible and universal remote control on the market today.

The remote control buttons are completely independent from each other, in this way it is possible to memorize, in 4 different keys, 4 different frequencies or 4 different brands, even all different from each other.

For each button you can store:

- Any Brand;
- Fixed codes;
- Rolling code.



Frequency	433 MHz
Channels	4 independent channels
Duplicable codes	Fixed and rolling codes
Diet	1 lithium battery 3 V - Type CR2032 (Included)
Dimensions	36 x 54 x 12 mm
Weight	30 g
Programming	Self-learning
Memory	Rewritable and resettable at any time

Duplication

1. Place the original remote control and the SUN.433 very close to each other;
2. Press and hold both the button of the original remote control to be cloned and the button of the SUN.433 on which you want to store the code until the LED of the SUN.433 starts flashing quickly;
3. TO at that point it is possible to release both buttons and the operation is completed;
4. Repeat the operation to duplicate other remote controls.

Delete the stored codes

1. Press and hold button 1 and button 2 of the SUN.433 until the LED starts flashing;
2. TO at that point keep button 1 pressed and in the meantime press button 2 three times.
3. For check the success of the operation simply press one of the buttons on which a code was previously stored and check that, when the button is pressed, the LED does not flash.

Restore deleted codes

Warning: this operation will only restore the last 4 codes deleted on the respective buttons.

1. Press and hold button 3 and button 4 of the SUN.433 until the LED starts flashing;
2. The led it will stop flashing, signaling the positive outcome of the operation.

Domotime srl

Via Monico, 9 25017 Lonato d / G (BS) - Italy -

Tel: +39 030 9913901 - Fax: +39 030 2070611

Skype: domotime - email: info@domotime.com - www.domotime.com